



IMPORTANT:
Turn off power to outlet.

IMPORTANTE: Desconecte corriente del circuito del desaque o toma.




GFCI
GFCI

1. Comes pre-configured for GFCI.
 2. Snap out desired ports using pliers.
- 1. Viene configurado previamente para GFCI.
2. Arranca los puertos de salida deseados usando pinzas.*



Duplex (Starts with GFCI Step 2)
Doble (Comienza con GFCI Paso 2)

1. Snap in the duplex adapter to the back of the base.
 2. Base ready for Duplex. Ready to mount to receptacle box.
- 1. Empuje con presión el adaptador dúplex a la espalda de la base.
2. La base que se muestra está configurada para el Doble. La base está lista para montarse a la caja que sirve de receptáculo.*



Adapter for Switch / Rounds (Starts with GFCI Step 2)
Adaptador para Interruptor / Redondo (Comienza con GFCI Paso 2)


1. Snap out round pieces on both sides for adapter.
2. Base is ready for adapter.
3. Adapter comes ready for switch. For rounds use pliers to snap out adapter rings.
4. Snap adapter to back of base. Base is then ready to mount to receptacle box.

- 1. Arranque las piezas circulares de ambos lados para el adaptador.
2. La base está lista para el adaptador.
3. El adaptador viene listo para la toma de corriente. Para los redondos, utilice pinzas para desprender los anillos del adaptador.
4. Fije el adaptador a la parte posterior de la base. La base está lista para montarse a la caja que sirve de receptáculo.*

Mounting to Receptacle Box
Montarse a la Caja



Back out receptacle screws. Do not remove screws.
Dé vuelta a los tornillos del receptáculo para aflojarlos, pero no los saque



Align screws with slots on base. Slide on base. Tighten screws.
Alinee los tornillos con las ranuras de la base. Deslice sobre la base. Apriete los tornillos.



Slide cover hinges onto base hinges, until they snap together.
Deslice las bisagras de la cubierta encima de las bisagras de la base, hasta que cierren juntas.

IMPORTANT: Turn off power to receptacle at the circuit breaker box or equivalent.
NOTE: Base should be installed on a smooth flat surface. To ensure a weather-proof seal on irregular surfaces such as brick or cedar siding, a 1/4 inch bead of non-hardening silicone caulk (not included) must be placed between the gasket and the mounting surface
WARNING: Improper installation of any electrical device can cause serious injury or death.

IMPORTANTE: Desconecte corriente del circuito del desaque o toma.

NOTA: La base deberá instalarse en una superficie suave y plana. A fin de garantizar un sello a prueba de agua en superficies irregulares, tales como ladrillo o tablas de cedro, se deberá colocar un reborde de 1/4 de pulgada de calafateo de silicona (no incluido) flexible entre el empaque y la superficie de montaje.

AVISO: Instalación incorrecta del algún aparato eléctrico puede causar heridas graves o hasta la muerte.

Required by NEC 406(B)(2) for use in wet locations while cord is plugged in.
Adapter, Gasket, & Screws Included.
Receptacles Not Included.