

5.10 Metering Products

Meter Breakers

Product Selection

House Panels



400A "House Panels"

5

Ampere Rating	Security ①	Bypass ②	Main Breaker	Optional Secondary Main Breaker (Not Included)	Service Type	kAIC	Dist.	Line Side Main Lugs and Neutral (Lugs Not Included)	Semi-Flush Catalog Number ③	Surface Catalog Number
300	Ringless	Lever	CSR2150	BW/CSR	OH/UG	22	8/16	Lug landings for compression	—	HP816P400BSL
300	Ringless	Lever	CSR2150	BW/CSR	UG	22	None		—	HPC30SHL
400	Ring	None	CSH2200N	CSR	UG	22	32/42	—	—	CG403242SH
400	Ring	None	CSH2200N	CSR	UG	22	12/12	—	—	CG1212P400BS ⑤
400	Ring	Manual	CSR2200	BRH/CSR	UG	22	None	—	—	HP40SHA ⑥
400	Ring	Manual	CSR2200	BRH/CSR	UG	22	40/40	—	—	HP404040SHA ⑥⑧
400	Ringless	None	DK2400	None	UG	22	24/40	—	—	HP402440B ⑦
400	Ringless	None	CSR2200	BRH/CSR	UG	22	24/40	—	—	HP402440SBH ⑦⑧
400	Ring	None	DK2400	None	UG	22	None	—	—	HP40
400	Ring	None	CSR2200	BRH/CSR	UG	22	None	—	—	HP40SH ⑧
400	Ring	None	DK2400	None	UG	22	24/42	—	—	HP402442
400	Ring	None	CSR220	BRH/CSR	UG	22	40/40	—	HP404040SHF	HP404040SH ⑧
400	Ring	Manual	CSR2200	BRH/CSR	UG	22	40/40	—	HP404040SHFA ⑥	—
400	Ring	None	CSR2200	BRH/CSR	UG	22	8/16	—	—	HP816P400BS ⑤⑧
400	Ringless	Lever	CSH2200N	CSR	UG	22	12/12	—	—	CG1212P400BSL ⑤
400	Ringless	Lever	CSH2200N	CSR	UG	22	42/42	—	—	CG404242SHL
400	Ringless	Lever	CSR2200	BRH/CSR	UG	22	None	—	—	HP40SHL ⑥
400	Ringless	Lever	CSR2200	BRH/CSR	OH/UG	22	None	—	—	HPC40SHL ⑥
400	Ringless	Lever	CSR2200	BRH/CSR	UG	22	40/40	—	—	HP404040SHL ⑥
400	Ringless	Lever	CSR2200	BRH/CSR	UG	22	8/16	—	—	HP816P400BSL ⑤⑧
400	Ringless	Lever	CSR2200	BRH/CSR	OH/UG	22	4/6	—	—	HPC4046SHLG ⑨
400	Ringless	Lever	CSR2200	BRH/CSR	OH/UG	22	4/6	—	—	HPC4046SHLX ⑩

Notes

- ① Confirm security type for individual EUSERC utility requirements.
- ② Included in all of the following devices.
- ③ If unit needs to be semi-flush, order accessory item catalog number **HPPR** to convert **all** surface mounting devices to semi-flush mounting.
- ④ Secondary sub-main installed in panel.
- ⑤ Feed-through lugs included.
- ⑥ Includes manual bypass and additional ground lug to meet Nevada Power requirements.
- ⑦ Bolt-on meter socket.
- ⑧ For 10 kAIC, use BR or BW breakers as secondary main.
- ⑨ Georgia Power approved.
- ⑩ Xcel approved