

ALL

Cold Shrink Jacket Seal Restoration

200ECS-G3



Features:

- Cold shrink jacket seal restoration kit.
- Easy to use place and pull install.
- Provides sealing and protection on extruded shield cable.
- Comes with constant force spring and wire braid.

200ECS-G3 Cold Shrink Jacket Seal Restoration

Applications:

The 200ECS-G3 Cold Shrink Jacket Seal Restoration system is used with XLP, EPR, or other similar solid dielectric insulated power cables. The 200ECS-G3 is compatible with extruded shield, such as copper tape shield cables, and provides the necessary shielding for the compromised cable. The 200ECS-G3 can be used with a variety of Elastimold products including:

- 165LR
- 275LR
- 15PCJ

Ratings:

Meets ANSI/IEEE Standard 386, Latest Revision
15kV Voltage Class
8.3kV Max Phase-to-Ground – Operating Voltage
14.4kV Max Phase-to-Phase
95kV BIL – Impulse Withstand (1.2 x 50 microsecond wave)
34kV AC – One minute withstand
53kV DC – 15 minutes withstand
11kV AC – Corona Extinction @ 3pC sensitivity
200 Amp – Continuous and Loadbreak
10kA Sym – 10 Cycles Momentary & Fault Close

25kV Voltage Class
15.2kV Max Phase-to-Ground – Operating Voltage
26.3kV Max Phase-to-Phase
125kV BIL – Impulse Withstand (1.2 x 50 microsecond wave)
40kV AC – One minute withstand
78kV DC – 15 minutes withstand
19kV AC – Corona Extinction @ 3pC sensitivity
200 Amp – Continuous and Loadbreak
10kA Sym – 10 Cycles Momentary & Fault Close

35kV Voltage Class
21.1kV Max Phase-to-Ground – Operating Voltage
36.6kV Max Phase-to-Phase
150kV BIL – Impulse Withstand (1.2 x 50 microsecond wave)
50kV AC – One minute withstand
103kV DC – 15 minutes withstand
26kV AC – Corona Extinction @ 3pC sensitivity
200 Amp – Continuous and Loadbreak
10kA Sym – 10 Cycles Momentary & Fault Close

ALL	Cold Shrink Jacket Seal Restoration	200ECS-G3
-----	--	------------------



Jacket Outside Diameter Range

Min	Max
0.80"	1.50"

Ordering Instructions:

To order jacket seal restoration kit, specify number **200ECS-G3**.

Each kit contains the following:

- 1 Jacket Seal Restoration 200ECS-G3

Notes:

To add the 200ECS-G3 to any part number just add the suffix "-SG3" to any already configured part number.