

Eaton AN16SN0CB

Catalog Number: AN16SN0CB

Eaton Freedom NEMA motor control starter, NEMA Freedom Series Non-Reversing Reset Overload Relay Starter, 75 hp at 208V, 100 hp at 240V, 200 hp at 480,600V maximum horsepower, 480V/60 Hz or 440V/50 Hz coil voltage, 270A, Three-pole, Size 5



General specifications

| | |
|--|-----------------------|
| Product Name | Catalog Number |
| Eaton Freedom NEMA motor control starter | AN16SN0CB |
| | UPC |
| | 782113971896 |

| | |
|-----------------------------|-----------------------|
| Product Length/Depth | Product Height |
| 7.75 in | 7.22 in |

| | |
|----------------------|-----------------------|
| Product Width | Product Weight |
| 12 in | 25 lb |

| | |
|-----------------|-----------------------|
| Warranty | Certifications |
|-----------------|-----------------------|

Eaton Selling Policy 25-000, one (1) year UL Listed

from the date of installation of the Product or eighteen (18) months from the

date of shipment of the Product,

whichever occurs first.

CSA Certified

[Catalog Notes](#)

Heater Packs must be purchased separately

defaultTaxonomyAttributeLabel

Special features

Starter w/C306 bi-metal OLR

Phase

Three-phase

Amperage Rating

270A

Size

5

Horsepower

75 hp at 208 V, 100 hp at 240 V, 200 hp at 480/600 V

Mounting

Horizontal

Resources

Catalogs

[Eaton's Volume 5—Motor Control and Protection](#)

Drawings

[AN16SN0_B AutoCAD 2D Footprint](#)

[AN16SN0_B 2D Drawing Xchange](#)

[AN16SN0_B AutoCAD 2D Footprint \(mm\)](#)

[AN16SN0_B 3D Inventor](#)

[AN16SN0_B 3D Model Xchange](#)

[AN16SN0_B 2D PDF](#)

Specifications and datasheets

[Quick Selector - NEMA Contactors](#)

[Eaton Specification Sheet - AN16SN0CB](#)



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



[Eaton.com/socialmedia](https://www.eaton.com/socialmedia)