

## 87164 - GES400MLTAA4-5

GE HID Distributor Replacement Kit Magnetic High Pressure Sodium Core and Coil Ballast

- Magnetic ballast construction ideal for a wide variety of lighting applications.
- Precision-wound aluminum coils, ensuring even heat dissipation and the highest electrical integrity
- Distributor replacement kit contains the appropriate core & coil with color coded leads, a properly rated capacitor and ignitor (if required) and all other components required for ballast replacement
- Quad ballast (120, 208, 240, 277)





### **CAUTIONS & WARNINGS**

### Warning

- Risk of Electric Shock
- Properly ground ballast and fixture.
- Turn power off before servicing--see instructions.

\*GE Lighting warrants to the purchaser that each ballast will be free from defects in material or workmanship for period as defined in the attached documents from the date of manufacture when properly installed and under normal conditions of use.

## **GENERAL CHARACTERISTICS**

Lamp Type HID - Bulb Magnetic

Ballast Type High Pressure Sodium Core

and Coil

Type Replacement kit

Dimming Type

N/A

Starting Method

Pulse start

Lamp Wiring

Series

Line Voltage Regulation (+/-)

Ambient Temperature (MIN)

Ambient Temperature (MAX)

N/A

Pulse start

10.0 %

-40.0 °C

105.0 °C

Ballast Factor 1
Circuit Type CWA

Insulation Class

Enclosure Type

Capacitance

Capacitror Temperature Rating

Distance to Lamp (MAX)

UL Class H 180

Core and Coil

55.0 µF

105.0 °C

10.0 ft

# **ELECTRICAL CHARACTERISTICS**

Lamp Operating Frequency 60.0 Hz Supply Current Frequency 60.0 Hz Voltage (MIN) 240.0

## **DIMENSIONS**

Weight 12.4 lb

 Exit Type

 Diameter
 1.750 in(44.4 mm)

 Nominal Length
 4.250 in(107.9 mm)

 Frame size (H x L)
 NaN in(NaN mm)

### **PRODUCT INFORMATION**

Product Code 87164

Description GES400MLTAA4-5

ANSI Code S51 Standard Package Master

Standard Package GTIN
Standard Package Quantity

Sales Unit Distributor Kit

No Of Items Per Sales Unit 1 No Of Items Per Standard 3

Package

UPC 043168871648

#### NOTES

• Kit contains the appropriate core & coil with color coded leads, a properly rated capacitor and ignitor (if required) and all other components required for ballast replacement