

97629 - F32TBX/827/A/ECO

GE Ecolux® Biax® T4 - Facilities; Retail Display; Hospitality; Office; Restaurant; Warehouse










CAUTIONS & WARNINGS

Caution

- Lamp may shatter and cause injury if broken
- Remove and install by grasping only plastic portion of the lamp.

GRAPHS & CHARTS

Graphs_Spectral Power Distribution



GENERAL CHARACTERISTICS

Lamp Type Compact Fluorescent - Plug-In

Bulb T4
Base GX24q-3
Equivalent Wattage 150.0 W
Rated Life 17000.0 hrs
Starting Temperature (MIN) 0.0 °C
Cathode Resistance 2.7 Ohm

LEED-EB MR Credit 87 picograms Hg per mean

lumen hour

Rated Life (rapid start) @ Time 17000.0 @ 3.0/20000.0 @

12.0 h

Additional Info Dimmable with appropriate

dimming ballast./End of Life Protection (EOL)/TCLP

compliant

20.0 Hz

Primary Application Facilities; Retail

Display;Hospitality;Office;Restaurant;W

PHOTOMETRIC CHARACTERISTICS

Initial Lumens2400.0Mean Lumens2040.0Nominal Initial Lumens per Watt75Color Temperature2700.0 KColor Rendering Index (CRI)82.0

ELECTRICAL CHARACTERISTICS

 Wattage
 32.0

 Voltage
 120.0

 Current (max)
 5.25 A

 Open Circuit Voltage (after preheating) (MAX)
 265.0 V

 Open Circuit Voltage (MIN)
 515.0 V

 Lamp Current
 0.32 A

 Preheat Voltage (MIN)
 4.25 V

DIMENSIONS

Supply Current Frequency

Maximum Overall Length 5.5000 in(139.7 mm)

(MOL)

Nominal Length 5.500 in(139.7 mm) Bulb Diameter (DIA) 4.750 in(120.6 mm)

PRODUCT INFORMATION

Product Code 97629

Description F32TBX/827/A/ECO ANSI Code 60501-IEC-7432-2

Standard Package Case

Standard Package GTIN 10043168976296

Standard Package Quantity

Sales Unit

No Of Items Per Sales Unit

No Of Items Per Standard

10

Package

UPC 043168976299

NOTES

- 4-Pin lamp minimum starting temperature is a function of the ballast. Most ballasts are rated with a minimum starting temperature of 50 degrees F (10 C). Ballasts are also available that provide reliable starting to 0 degrees F (-18C) and -20 F (-29C).
- Amalgam product experience stable brightness over a wider temperature range and in various operating positions.
- Based on 60Hz reference circuit
- Fluorescent lamp lumens decline during life