



MR16, MR11, MR16 SIG 64005



PAR36

**TRU-AIM® MR16 LAMPS**

UV Filter capsule with axial filament in covered dichroic reflector.

Watts	Bulb	Base	Product Number	Symbols & Footnotes	Ordering Abbreviation	Volts	Pkg Qty	Beam Type	Class & Filament	Avg Rated Life(hrs)	Lumens CCT	CBCP	Beam Angle	MOL (in)
50	MR16	GU5.3 Bipin	58326	45,62,92,93,145	<b>50MR16/NFL25(C)(EXZ)</b>	12	20	NFL	C, AXIAL	2000	3000	2800	25	1.75
			58327	45,62,92,93,145	<b>50MR16/FL35(C)(EXN)</b>	12	20	FL	C, AXIAL	2000	3000	1450	35	1.75
			58328	45,62,92,93,145	<b>50MR16/WFL60(C)(FNV)</b>	12	20	WFL	C, AXIAL	2000	3000	690	60	1.75

**TRU-AIM® MR11 LAMPS**

UV Filter capsule with axial filament in covered constant color, hard coated dichroic reflector.

Watts	Bulb	Base	Product Number	Symbols & Footnotes	Ordering Abbreviation	Volts	Pkg Qty	Beam Type	Class & Filament	Avg Rated Life(hrs)	Lumens CCT	CBCP	Beam Angle	MOL (in)
20	MR11	GU4 Bipin	55133	62,65,92,93	<b>20MR11/T/SP10(C)(FTB)</b>	12	10	SP	C, AXIAL	4000	3000	4000	10	1.50
			55134	62,65,92,93	<b>20MR11/T/FL35(C)(FTD)</b>	12	10	FL	C, AXIAL	4000	3000	700	35	1.50
35	MR11	GU4 Bipin	55135	62,65,92,93	<b>35MR11/T/SP10(C)(FTE)</b>	12	10	SP	C, AXIAL	4000	3000	6200	10	1.50
			55136	62,65,92,93	<b>35MR11/T/FL35(C)(FTH)</b>	12	10	FL	C, AXIAL	4000	3000	1350	35	1.50

**SIRIUS MR16 LAMPS**

For traffic signal and other fiber optic applications.

Watts	Bulb	Base	Product Number	Symbols & Footnotes	Ordering Abbreviation	Volts	Pkg Qty	Beam Type	Class & Filament	Avg Rated Life(hrs)	Lumens CCT	CBCP	Beam Angle	MOL (in)
50	MR16 SIG 64005	K23D	58701	32,117	<b>50SIRIUS/SIG64005</b>	10	10		C, AXIAL	6000	220 3000			1.88

**CAPSYLITE® PAR36 LAMPS**

Suitable for use in unshielded fixtures.

Watts	Bulb	Base	Product Number	Symbols & Footnotes	Ordering Abbreviation	Volts	Pkg Qty	Beam Type	Class & Filament	Avg Rated Life(hrs)	Lumens CCT	CBCP	Beam Angle	MOL (in)
36	PAR36	Screw Term	55100	★  73	<b>36PAR36/HAL/VNSP5</b>	12	12	VNSP	C, C-8	4000	500 3000	17000	5	2.75
			55090	★  73	<b>36PAR36/HAL/NSP13</b>	12	12	NSP	C, C-8	4000	500 3000	3500	13	2.75
			55091	★  73	<b>36PAR36/HAL/WFL32</b>	12	12	WFL	C, C-8	4000	500 3000	1000	30	2.75
50	PAR36	Screw Term	55118	★  73	<b>50PAR36/HAL/NSP6</b>	12	12	NSP	C, C-8	4000	700 3000	25000	6	2.75
			55017	★  73	<b>50PAR36/HAL/WFL30</b>	12	12	WFL	C, C-8	4000	700 3000	1400	30	2.75