



QH1000S

QL100

Q-Lume™

Revealing a better way

Utility Jar Fixture with Hub Water/Airtight, High Pressure Washable

Part Numbers

Assembled:	
Q-Lume Fixture	QL100JS, QL100J
Q-Lume Fixture. No Globe	QL103S, QL103

Parts:

Q-Hub w/ & w/o	screw	QH1000S, QH1000
Q-Lume Subasser	nbly	QL100
Clear Glass Jar		QLJAR

Application:

The most watertight utility jar fixture available today. Assembled with our Q-Hub, the Q-Lume is designed for the barn and those that wire and repair barn lighting. Together they are perfect for new construction projects. Installs four times faster! Gaskets are all captive, made with high temp silicone - ensuring long life, frustration free installation, and a waterproof fit. The FicientLock™ System requires no screws so future repairs are quick and easy.

Features:

- No assembly screws
- FicientLock™ System
- Includes captive gaskets
- · Replaceable nickel plated socket
- Pre-installed mounting screw
- 3/4" knockouts/conduit hubs, (2) open at 180°,
 (2) closed
- Direct glue to PVC, no fittings required
- · Corrosion resistant, air and watertight

FicientLock™ Technology



Q-Lume



Q-Hub

Q-Lume #QL100



lass Glok #QLJAR



EnvironmentalSuitable for wet or damp locations

Safety ETL listed, Certified to UL Std. 1598, Certified to CAN/CSA 22.2 #250.0

Wattage40W Max, Incandescent, CFL or LED lamps

Hubs(2) open 3/4" hubs and (2) knockout type at 180°

Socket Replaceable E26 medium base, nickel plated

PackagingQL100JS: 12 per box; Box Size: 23.75" x 18.75" x 10"; Weight: 22 lbs



7 1/2"



materials

ETL listed for





wet locations outdoor use