



[Catalog Home](#)

Product Datasheet

CHANCE

M140KA -- Type K (ANSI) Cutout Fuselink



140 amp, Type K (ANSI) Cutout fuselink with a 26" (660.4mm) pigtail and a removable buttonhead.

Product Specifications

Type	Fuselinks
Fuselinks	Type K (ANSI)
Amp Rating	140
Removable Buttonhead	Yes
Pigtail Length	26" (660.4mm)
Twin Pigtails (140A and 200A only)	No
PDF Catalog Page	Click HERE to view detailed PDF Catalog
Fuse Link Application Guide and Time-Current Curves	Click HERE and request, Fuse Links (Bulletin 10-7701).
Fuse Element	Silver-copper fuse wire
Required Cutout Fuseholder	200 Amp (Do not use in a 100 amp fuseholder.)
Material Type	Non-Standard
UPC Code	09635904332
Standard Package	5
Standard Package Unit	Each
Min Order Qty	5
Pallet Quantity	100
Weight / Ea.	0.5 lbs

Compressed Product Number

M140KA

[Catalog Home](#)



[Warranty Info](#) | [Trademarks](#) | [Terms of Use](#)

All contents Copyright © 2007 Hubbell Power Systems, Inc. All rights reserved.

NOTE: Because Hubbell has a policy of continuous product improvement, we reserve the right to change design and specifications

