Switched Disconnects and Enclosures



CPB Series Compact Pendant Stations, Two Button, NEMA 4X

Description	Catalog Number
Single-speed normally open-normally closed without mechanical interlock.	CPB20
Single-speed with mechanical interlock between pushbuttons.	CPB21
Single-speed with mechanical interlock between pushbuttons, black housing.	CPB21BK
Two-speed with mechanical interlock between pushbuttons.	CPB22

Note: Included with product: nylon cord grip and sealing washer (must be installed to achieve NEMA 4X rating). Indication label pack. Cord dia. range .375–.625 in. (9.5–15.9)
Ambient temperatures: 25°F to 140°F (32°C to 60°C).

Typical applications: Package electric motor hoists. Remote control of machinery.

Contact Ratings, CPB Series

Single-Speed	Voltage	Current
AC	120V	6A
35% PF	240V	ЗА
DC	125V	1.1A
IND	250V	.55A
Two-Speed	Voltage	Current
AC	120V	ЗА
35% PF	240V	1.5A




<u>IP55</u>

Wiring Diagram CPB2 Series

CPB21

9.13" (231.9)



*Mechanical "floating ball" interlock prevents activating both Pushbuttons simultaneously.

PBS Series Heavy Duty Pendant Pushbutton Stations, NEMA 3R

Description	Catalog Number
2 button, single speed.	PBS2
2 button, two speed.	PBS22
4 button, single speed.	PBS4
4 button, two speed.	PBS42
6 button, single speed.	PBS6
6 button, two speed.	PBS62
8 button, single speed.	PBS8
8 button, two speed.	PBS82

Product Dimensions, PBS Series


Style	А	Approx. Wt. Assembled	Catalog Number
2 button	7.88" (200.0)	2.5 lbs	PBS2
4 button	13.69" (347.6)	4.5 lbs	PBS4
6 button	18.0" (457.2)	5.5 lbs	PBS6
8 button	22.31" (566.7)	7.5 lbs	PBS8

Note: Housing: Yellow vinyl rubber.

Contact Interrupting Ratings, PBS Series

<u> </u>		
Two-Speed Single Break	Voltage	Current
AC	120V	6A
35% PF	240V	3A
DC	125V	.4A
IND	250V	.2A
Single-Speed Double Break	Voltage	Current
AC	120V	6A
35% PF	240V	3A
DC	125V	1.1A
IND	250V	.55A





Dimensions in Inches (mm)