



Product Number: 47676

Order Abbreviation: M320/MULTI-PS-KIT

General Description: 120/208/240/277V multi-tap magnetic core and coil pulse start ballast for 320W pulse start metal halide lamp

*** Full Case Required**

Product Information

Abbrev. With Packaging Info.	M320MULTIPSKIT 1/CS 1/SKU
ANSI Code	M132
Circuit Type	CWA
Nominal Voltage (V)	120/208/240/277V
Number of Lamps	1
Open Circuit Voltage (V)	270
Power Factor	>0.9
Primary Lamp Type	M320/PS
Sound Rating	N
Starting Method	PULSE IGNITOR
Starting Temperature - Fahrenheit	-22°F
Starting Temperature - Celsius	-30°C
Total Harmonic Distortion (THD)	<20%
Wiring Method	LEADS
Total Maximum Wattage	368



Footnotes

- Product is a kit containing the core & coil, capacitor, ingitor (where required), brackets and mounting hardware
- Install in accordance with National Electric Codes
- High Voltage Pulse Present on Open Circuit
- Ground Ballast Core and Metallic Case of Capacitor and Ignitor
- Minimum starting temperature: -20 F / -29 C
- Product contains installation instructions