



GE
Lighting

87211 - GEM250ML5AC3-5

GE HID Distributor Replacement Kit Magnetic Core & Coil Ballast

- Magnetic ballast construction ideal for a wide variety of lighting applications.
- Precision-wound coils, ensuring even heat dissipation and the highest electrical integrity.
- Distributor replacement kit contains the appropriate core & coil with color coded leads, a properly rated capacitor and ignitor (if required) and all other components required for ballast replacement
- Multi-5 ballast (120, 208, 240, 277, or 480 Volt) featuring a 480-Volt tap.



CAUTIONS & WARNINGS

Warning

- Risk of Electric Shock
 - Properly ground ballast and fixture.
 - Turn power off before servicing--see instructions.

NOTES

- Kit contains the appropriate core & coil with color coded leads, a properly rated capacitor and ignitor (if required) and all other components required for ballast replacement

GENERAL CHARACTERISTICS

Lamp Type	HID -
Bulb	Magnetic
Ballast Type	Core & Coil
Type	Replacement kit
Line Voltage Regulation (+/-)	10.0 %
Ballast Factor	Normal
Circuit Type	CWA
Insulation Class	180C
Enclosure Type	None
Capacitance	15.0 μ F
Capacitor Temperature Rating	100.0 $^{\circ}$ C

ELECTRICAL CHARACTERISTICS

Supply Current Frequency	60.0 Hz
Voltage (MIN)	400.0

DIMENSIONS

Weight	9.0 lb
Exit Type	
Diameter	1.750 in(44.4 mm)
Nominal Length	3.250 in(82.6 mm)
Frame size (H x L)	NaN in(NaN mm)

PRODUCT INFORMATION

Product Code	87211
Description	GEM250ML5AC3-5
Standard Package	Master
Standard Package GTIN	
Standard Package Quantity	6
Sales Unit	Distributor Kit
No Of Items Per Sales Unit	1
No Of Items Per Standard	6
Package	
UPC	043168872119