




GE  
Lighting

## 87213 - GEM1000ML5AA5-5

### GE HID Distributor Replacement Kit Magnetic Core & Coil Ballast

- Magnetic ballast construction ideal for a wide variety of lighting applications.
- Precision-wound coils, ensuring even heat dissipation and the highest electrical integrity.
- Distributor replacement kit contains the appropriate core & coil with color coded leads, a properly rated capacitor and ignitor (if required) and all other components required for ballast replacement
- Multi-5 ballast (120, 208, 240, 277, or 480 Volt) featuring a 480-Volt tap.



#### CAUTIONS & WARNINGS

##### Warning

- Risk of Electric Shock
  - Properly ground ballast and fixture.
  - Turn power off before servicing--see instructions.

#### NOTES

- Kit contains the appropriate core & coil with color coded leads, a properly rated capacitor and ignitor (if required) and all other components required for ballast replacement

#### GENERAL CHARACTERISTICS

Lamp Type	HID -
Bulb	Magnetic
Ballast Type	Core & Coil
Type	Replacement kit
Line Voltage Regulation (+/-)	10.0 %
Ballast Factor	Normal
Circuit Type	CWA
Insulation Class	180C
Enclosure Type	None
Capacitance	24.0 $\mu$ F
Capacitor Temperature Rating	100.0 $^{\circ}$ C

#### ELECTRICAL CHARACTERISTICS

Supply Current Frequency	60.0 Hz
Voltage (MIN)	480.0

#### DIMENSIONS

Weight	21.0 lb
Exit Type	
Remote Mounting Distance	3.0E-37
Remote Mounting Wire Gauge	3.0E-37
Diameter	2.000 in(50.8 mm)
Nominal Length	3.750 in(95.2 mm)
Frame size (H x L)	NaN in(NaN mm)

#### PRODUCT INFORMATION

Product Code	87213
Description	GEM1000ML5AA5-5
Standard Package	Master
Standard Package GTIN	
Standard Package Quantity	2
Sales Unit	Distributor Kit
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	2
UPC	043168872133