

31067 - GE ConstantColor® CMH® Ceramic Metal Halide ED17 CMH150U942MED/O

## **GENERAL CHARACTERISTICS**

Medium Screw

Open or enclosed fixtures

High Intensity Discharge

190 °C

400 °C

66.7

Clear

19

E26 FD17

9000 lm

80 lm 12000 lm

4200 K

31067

CASE

Case

2.13 in 3.38 in

5.43 in

CMH150U942MED/O

043168310673 10043168310670

043168310673

90

15000 h

Hard glass

Screw-In

**Base Description** Base Temp C-degrees (MAX) Base Type Bulb Temperature C-degree(MAX) Lamp Enclosure Type (LET) Mercury-Picogrm per mean Im hr Rated Life Hours-nominal **Bulb Finishes and Colors** Mercury Content EMEA ONLY **Bulb Material** Product Technology Base **Bulb Shape** 

### PHOTOMETRIC CHARACTERISTICS

Mean Lumens nominal Nominal Lumens per Watt Initial Lumens-nominal Color Rendering Index-CRI Color Temperature

## **PRODUCT INFORMATION**

Product Code Description Alternative Unit Of Measure Standard Package Quantity Ean UPC Standard Package GTIN No Of Items Per Sales Unit No Of Items Per Standard Package Sales Unit UCC

### DIMENSIONS

Diameter Light Center Length Millimeter Nominal Length

# **ELECTRICAL CHARACTERISTICS**

Burn Position	Universal burning position
Hot Restart Time to 90%MAX	15 min
Rated power (Watts)	150 W

### **CAUTIONS & WARNINGS**

WARNING: This lamp can cause serious skin burn and eye inflammation from shortwave ultraviolet radiation if outer envelope of the lamp is broken or punctured, and the arc tube continues to operate. Do not use where people will remain for more than a few minutes unless adequate shielding or other safety precautions are used. Certain types of lamps that will automatically extinguish when the outer envelope is broken or punctured are commercially available. Visit the FDA website for more information: http://www.fda.gov/cdrh/radhealth/products/urburns.html

#### Caution

Lamp may shatter and cause injury if broken

Dispose of lamp in a closed container.

Do not use excessive force when installing lamp.

Do not use lamp if outer glass is scratched or broken.

#### Warning

A damaged lamp emits UV radiation which may cause eye/skin injury

Turn power off if glass bulb is broken. Remove and dispose of lamp.

**Risk of Electric Shock** 

Do not use where directly exposed to water or outdoors without an enclosed fixture.

Turn power off before inspection

installation or removal.

### Risk of Burn

Allow lamp to cool before handling.

Do not turn on lamp until fully installed.

# Risk of Fire

Keep combustible materials away from lamp.

Use in fixture rated for this product.

Unexpected lamp rupture may cause injury, fire, or property damage

Do not exceed rated voltage.

Do not store flammable materials near/below S-rated lamp in open fixture

Do not turn on lamp until fully installed.

Do not use beyond rated life.

Do not use lamp if outer glass is scratched or broken.

Do not use where directl

## NOTES

Rated life based on 11 hours per start

Sep 27, 2017 6:37:20 PM For additional information, visit www.gelighting.com