

Products

- > [Index](#)
- > [Featured Products](#)
- > [Cross Reference](#)
- > [UPC Search](#)

**Product Datasheet**

[Catalog Home](#)

[Home Page](#)

[Search](#)

**196 -- 4" Square Box, 1-1/2" Deep, 1/2" & 3/4" Side Knockouts, Universal Wood/Metal Stud Bracket, Welded**



**Product Specifications**

<b>Box Type</b>	RACO Steel Boxes & Covers
<b>Box Family</b>	4" Square Boxes, Covers, Extension Rings
<b>Box Category</b>	4" Square Boxes - For Conduit
<b>Category</b>	4" Square Box
<b>Wiring System</b>	Conduit
<b>Box Depth</b>	1-1/2"
<b>Side Knockout(s)</b>	6, 1/2" & 3, TKO
<b>Bottom Knockout(s)</b>	3, 1/2" & 2, TKO
<b>Bracket Type</b>	Universal For wood or metal studs

<b>Bracket Setback</b>	Flush
<b>Drawn or Welded</b>	Welded
<b>Cubic Inch Capacity</b>	21.0
<b>UPC Number</b>	050169901960
<b>Product UPC-A Labeled</b>	No
<b>Minimum Pack Qty.</b>	25
<b>Max. Recommended Support Load, Fixture (Static)</b>	50 lbs.
<b>Inner Leaf 2 of 5 Bar Code</b>	50050169901965
<b>Unit Carton Quantity</b>	25
<b>Ship Carton Length (In.)</b>	16.125
<b>Ship Carton Width (In.)</b>	11.25
<b>Ship Carton Height (In.)</b>	7.75
<b>Weight (Per/C)</b>	81.2
<b>Pallet Quantity</b>	1650
<b>Fire Resistance</b>	Acceptable for use in 2-hour rated walls
<b>Dimension A</b>	1-1/2"
<b>Dimension B</b>	6-7/8"
<b>Dimension C</b>	4-3/8"

#### Applications

- Boxes are installed in ceilings or walls for lighting fixtures, switches or receptacles
- Square boxes are used where multiple conductor runs are split into two or more directions to bring power to a number of electrical devices

#### Product Features

- Features RACO's patented TKO 1/2" & 3/4" eccentric knockouts (Per U.L. 514-A, suitable for use without a bonding jumper in circuits above or below 250 volts)
- Combination cover screw heads provide for faster mudring/cover installation
- Universal bracket mounts flat on side of wood or metal stud and provides a rigid/secure box installation

#### Compliances

UL 514-A listed, File E195978

#### Country of Origin

MADE IN THE U.S.A.

