

Eaton BR4040NC200R

Catalog Number: BR4040NC200R

Eaton BR convertible loadcenter, Current design, Convertible main, 200 A, 6, Copper, Cover not included, NEMA 3R, Metallic, 10 kAIC, Flush, 40 Circuits, Four-pole, 40 Spaces, Three-wire, Single-phase, Type BR 1-inch breakers, 120/240 V



General specifications

Product Name	Catalog Number
Eaton BR convertible loadcenter	BR4040NC200R
UPC	Product Length/Depth
786676449151	4.5 in
Product Height	Product Width
12 in	6.88 in
Product Weight	Warranty
49 lb	10 year
Certifications	Catalog Notes
UL 50 UL 67	The maximum rating of the panel is the main breaker rating when used as service entrance equipment.

defaultTaxonomyAttributeLabel

Special features

Current design

Type

Convertible main

Amperage Rating

200 A

Bus material

Copper

Cover

Cover not included

Mounting

Flush

Number of circuits

40

Number Of Poles

Four-pole

Number of spaces

40

Phase

Single-phase

Used with

Type BR 1-inch breakers

Voltage rating

120/240 V

Wire size

Determined by circuit breaker installed

Box size

6

Enclosure

NEMA 3R

Enclosure material

Metallic

Interrupt rating

10 kAIC

Resources

Brochures

Loadcenters and Circuit Breakers

Type BR Arc Fault Circuit Breakers and Loadcenters

Catalogs

Eaton's Volume 1—Residential and Light Commercial

Drawings

Dimensional Drawing - BR 1 LOADCENTER, CSR CONVERTIBLE, OUTDOOR NEMA 3R, 120/240 VAC, 1 PHASE

Installation instructions

Cutler-Hammer Type CH and BR Loadcenters - Instructions

Specifications and datasheets

Eaton Specification Sheet - BR4040NC200R

Number of wires

3



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



Eaton.com/socialmedia