

Eaton CH2L40FP

Catalog Number: CH2L40FP

Eaton CH main lug loadcenters, Standard, Main lug only, 40A, 5, Copper, NEMA 1, Metallic, Top/bottom, CH, Flush, 2, Four-pole, 2, Three-wire, Single-phase, 120/240 V, #14-6 AWG



General specifications

Product Name

Eaton CH main lug loadcenter

Catalog Number

CH2L40FP

UPC

782114190401

Product Length/Depth

9.5 in

Product Height

3.13 in

Product Width

4.5 in

Product Weight

5.8 lb

Warranty

Limited lifetime

Certifications

UL 67

UL 50

Catalog Notes

Ground bar kits priced separately.
Suitable for use as service equipment when not more than two service disconnecting mains are provided or when not used as a lighting and appliance panelboard.

[Special features](#)

Standard

[Type](#)

Main lug only

[Amperage Rating](#)

40 A

[Bus material](#)

Copper

[Feed type](#)

Top/bottom

[Main circuit breaker](#)

CH

[Mounting](#)

Flush

[Number of circuits](#)

2

[Number Of Poles](#)

Four-pole

[Number of spaces](#)

2

[Phase](#)

Single-phase

[Voltage rating](#)

120/240 V

[Wire size](#)

#14-6 AWG

[Box size](#)

5

[Enclosure](#)

NEMA 1

[Enclosure material](#)

Metallic

[Interrupt rating](#)

25 kAIC

[Number of wires](#)[Brochures](#)

Type CH Circuit Breakers and Loadcenters

Loadcenters and Circuit Breakers

[Catalogs](#)

Eaton's Volume 1—Residential and Light Commercial

[Installation instructions](#)

Cutler-Hammer Type CH and BR Loadcenters - Instructions

[Multimedia](#)

AFCI Educational Video

[Specifications and datasheets](#)

Eaton Specification Sheet - CH2L40FP



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com
© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are
property of their respective
owners.



[Eaton.com/socialmedia](https://www.eaton.com/socialmedia)