



GE  
Lighting

### 71703 - GEM400ML5AC4-55

#### GE HID Distributor Replacement Kit Magnetic Lamp and Ballast Kit Ballast

- GE Lamp & Ballast Kit includes standard GE lamp prewired core & coil ballast, capacitor, ignitor (if required), mounting bracket & hardware.
- Magnetic ballast construction ideal for a wide variety of lighting applications.
- Precision-wound coils, ensuring even heat dissipation and the highest electrical integrity.
- Distributor replacement kit contains the appropriate core & coil with color coded leads, a properly rated capacitor and ignitor (if required) and all other components required for ballast replacement
- Multi-5 ballast (120, 208, 240, 277, or 480 Volt) featuring a 480-Volt tap.



#### GENERAL CHARACTERISTICS

Lamp Type	HID -
Bulb	Magnetic
Ballast Type	Lamp and Ballast Kit
Type	Replacement kit
Line Voltage Regulation (+/-)	10.0 %
Ballast Factor	Normal
Circuit Type	CWA
Insulation Class	180C
Enclosure Type	None
Capacitance	24.0 $\mu$ F
Capacitor Temperature Rating	100.0 $^{\circ}$ C

#### ELECTRICAL CHARACTERISTICS

Supply Current Frequency	60.0 Hz
Voltage (MIN)	400.0

#### DIMENSIONS

Weight	11.9 lb
Exit Type	
Diameter	1.750 in(44.4 mm)
Nominal Length	3.750 in(95.2 mm)
Frame size (H x L)	NaN in(NaN mm)

#### PRODUCT INFORMATION

Product Code	71703
Description	GEM400ML5AC4-55
Standard Package	Case
Standard Package GTIN	10043168717035
Standard Package Quantity	1
Sales Unit	Distributor Kit
No Of Items Per Sales Unit	2
No Of Items Per Standard	2
Package	
UPC	043168717038

#### CAUTIONS & WARNINGS

##### Warning

- Risk of Electric Shock
  - Properly ground ballast and fixture.
  - Turn power off before servicing--see instructions.

##### NOTES

- Kit contains the appropriate core & coil with color coded leads, a properly rated capacitor and ignitor (if required) and all other components required for ballast replacement