



GE
Lighting

71707 - GES400ML5AC4-55

GE HID Distributor Replacement Kit Magnetic Lamp and Ballast Kit Ballast

- GE Lamp & Ballast Kit includes standard GE lamp prewired core & coil ballast, capacitor, ignitor (if required), mounting bracket & hardware.
- Magnetic ballast construction ideal for a wide variety of lighting applications.
- Precision-wound coils, ensuring even heat dissipation and the highest electrical integrity.
- Distributor replacement kit contains the appropriate core & coil with color coded leads, a properly rated capacitor and ignitor (if required) and all other components required for ballast replacement
- Multi-5 ballast (120, 208, 240, 277, or 480 Volt) featuring a 480-Volt tap.



GENERAL CHARACTERISTICS

Lamp Type	HID -
Bulb	Magnetic
Ballast Type	Lamp and Ballast Kit
Type	Replacement kit
Line Voltage Regulation (+/-)	10.0 %
Ballast Factor	Normal
Circuit Type	CWA
Insulation Class	180C
Enclosure Type	None
Capacitance	55.0 μ F
Capacitor Temperature Rating	100.0 $^{\circ}$ C
Distance to Lamp (MAX)	10.0 ft

ELECTRICAL CHARACTERISTICS

Supply Current Frequency	60.0 Hz
Voltage (MIN)	240.0

DIMENSIONS

Weight	15.0 lb
Exit Type	
Diameter	1.750 in(44.4 mm)
Nominal Length	4.250 in(107.9 mm)
Frame size (H x L)	NaN in(NaN mm)

PRODUCT INFORMATION

Product Code	71707
Description	GES400ML5AC4-55
Standard Package	Case
Standard Package GTIN	10043168717073
Standard Package Quantity	1
Sales Unit	Distributor Kit
No Of Items Per Sales Unit	2
No Of Items Per Standard Package	2
UPC	043168717076

CAUTIONS & WARNINGS

Warning

- Risk of Electric Shock
 - Properly ground ballast and fixture.
 - Turn power off before servicing--see instructions.

NOTES

- Kit contains the appropriate core & coil with color coded leads, a properly rated capacitor and ignitor (if required) and all other components required for ballast replacement