Product data sheet Characteristics

HOM115DF MINIATURE CIRCUIT BREAKER 120V 15A

Product availability: Stock - Normally stocked in distribution facility





Price*: 312.00 USD



Main

man		
Product or component type	Miniature circuit-breaker	
Range of product	Homeline	
Line Rated Current	15 A	
Product certifications	UL listed	- 5
System Voltage	120 V AC	
Mounting mode	Plug-in	
Poles description	1P	
Short-circuit current	10 kA	
Number of spaces required	1	
Circuit breaker type	Combination ARC-fault and ground fault	
Circuit breaker application	HACR rated	_
Electrical connection	Clamp terminal for 2 cables	
AWG gauge	AWG 14AWG 8 for 1 cable(s) (aluminium/copper) AWG 14AWG 10 for 2 cable(s) (copper)	

Ordering and shipping details

Main		
Product or component type	Miniature circuit-breaker	
Range of product	Homeline	
Line Rated Current	15 A	
Product certifications	UL listed	
System Voltage	120 V AC	
Mounting mode	Plug-in	
Poles description	1P	
Short-circuit current	10 kA	
Number of spaces required	1	
Circuit breaker type	Combination ARC-fault and ground fault	
Circuit breaker application	HACR rated	
Electrical connection	Clamp terminal for 2 cables	
AWG gauge	AWG 14AWG 8 for 1 cable(s) (aluminium/copper) AWG 14AWG 10 for 2 cable(s) (copper)	
Ordering and shipping details		
Category	06301 - HOM SINGLE POLE ARC FAULT CIRCUIT BREAKER	
Discount Schedule	DE3D	
GTIN	00785901741329	
Nbr. of units in pkg.	1	
Package weight(Lbs)	0.670000000000004	
Returnability	Υ	
Country of origin	MX	
,		
Offer Sustainability		
Sustainable offer status	Green Premium product	
RoHS (date code: YYWW)	Compliant - since 1412 - Schneider Electric declaration of conformity	
And 25, 2047		

Offer Sustainability

Sustainable offer status	Green Premium product	F
RoHS (date code: YYWW)	Compliant - since 1412 - Schneider Electric declaration of conformity	

Schneider Electric declaration of conformity

REACh	Reference contains SVHC above the threshold - Go to CaP for more details Go to CaP for more details
Product environmental profile	Available
Product end of life instructions	Available