

Eaton FAZ-C63{3}

Catalog Number: FAZ-C63/3

Eaton FAZ supplementary protector,UL 1077 Industrial miniature circuit breaker - supplementary protector,Medium levels of inrush current are expected,63 A,15 kAIC,Three-pole,5-10X /n,50-60 Hz,Standard terminals,C Curve



Photo is representative

General specifications

Product Name	Catalog Number
Eaton FAZ supplementary protector	FAZ-C63/3
EAN	Product Length/Depth
4015082788797	2.07 in
Product Height	Product Width
2.07 in	2 in
Product Weight	Warranty
0.8 lb	1 year
Certifications	Catalog Notes
CSA Std. C22.2 No.235	Positioned for medium inrush startup
IEC 60947-2	currents to provide protection for small
UL 1077	transformers and pilot devices.

Physical Attributes

Number of poles

Three-pole

Terminals

Standard

Type

UL 1077 Industrial miniature circuit breaker - supplementary protector

Performance Ratings

Amperage Rating

63 A

Circuit protection

C curve

Frequency rating

50-60 Hz

Interrupt rating

15 kAIC

Trip Type

5-10X /n

Miscellaneous

Application

Suitable for applications where medium levels of inrush current are expected

Resources

Brochures

[Industrial miniature circuit breakers UL 489](#)

Catalogs

[Eaton's Volume 4—Circuit Protection](#)

Specifications and datasheets

[Product Data Sheet - FAZ-C63/3](#)

[Eaton Specification Sheet - FAZ-C63/3](#)



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



Eaton.com/socialmedia