

# Eaton FAZ-C20/2-NA

Catalog Number: FAZ-C20/2-NA

Eaton FAZ branch protector, UL 489 Industrial miniature circuit breaker - supplementary protector, Medium levels of inrush current are expected, 20 A, 10 kAIC, 14 kAIC, Two-pole, 277/480 V, 5-10X /n, 50-60 Hz, Screw terminals, C Curve



Photo is representative

## General specifications

<b>Product Name</b>	<b>Catalog Number</b>
Eaton FAZ branch protector	FAZ-C20/2-NA
<b>UPC</b>	<b>EAN</b>
786689005160	4015081020478
<b>Product Length/Depth</b>	<b>Product Height</b>
1.4 in	4.13 in
<b>Product Width</b>	<b>Product Weight</b>
2.97 in	1 lb
<b>Warranty</b>	<b>Certifications</b>
1 year	UL 489 CSA Std. C22.2 No. 235

## Catalog Notes

Positioned for medium inrush startup currents to provide protection for small transformers and pilot devices.

## Physical Attributes

### Number of poles

Two-pole

### Terminals

Screw

### Type

UL 489 Industrial miniature circuit breaker - supplementary protector

## Performance Ratings

### Amperage Rating

20 A

### Circuit protection

C curve

### Frequency rating

50-60 Hz

### Interrupt rating

14 kAIC

10 kAIC

### Trip Type

5-10X /n

### Voltage rating

277/480V

## Miscellaneous

### Application

Suitable for applications where medium levels of inrush current are expected

## Resources

### Brochures

[Industrial miniature circuit breakers UL 489](#)

### Catalogs

[Eaton's Volume 4—Circuit Protection](#)

### Specifications and datasheets

[Eaton Specification Sheet - FAZ-C20/2-NA](#)

[Product Data Sheet - FAZ-C20/2-NA](#)



Eaton Corporation plc  
Eaton House  
30 Pembroke Road  
Dublin 4, Ireland  
Eaton.com  
© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



[Eaton.com/socialmedia](https://www.eaton.com/socialmedia)