

Model # 10035K

# ELECTRICAL TEST KIT

Combines the 3 most commonly used electrical testers in one convenient kit. Ideal for household repairs and electrical troubleshooting.

## 10030S MANUAL RANGING MULTIMETER

CAT III 600V Safety rating with double molded housing and includes battery testing function

## 40010S RECEPTACLE TESTER

Checks for miswired outlets



### 7 FUNCTIONS

- AC Voltage
- DC Voltage
- DC Current
- Resistance
- Battery Test
- Continuity
- Diode Test

## 40110N NON-CONTACT VOLTAGE DETECTOR

Check for live voltages.  
100 - 1000V AC with built in flashlight.



[southwiretools.com](http://southwiretools.com)

BUILT FOR DURABILITY. BUILT FOR RELIABILITY.  
**BUILT FOR WORK.**



**Southwire™**

## KIT INCLUDES

- 10030S Manual Ranging Multimeter with test leads
- 40110N Non-Contact AC Voltage Detector
- 40010S Receptacle Tester
- One 9 volt and two AAA batteries

## SPECIFICATIONS

MANUAL RANGING MULTIMETER (10030S)			
	Range	Max. Resolution	Basic Accuracy (% of reading)
AC Voltage:	600V	0.1V	±1.2%
DC Voltage:	600V	0.1mV	±0.8%
DC Current:	10A	1µA	±1.2%
Resistance:	2000kΩ	0.1Ω	±0.8%
Battery Test:	1.5V, 9V	10mV	±1.0%
Continuity:	Audible threshold: Approximately 30Ω		
Diode Test:	Yes		
Dimensions:	5.44 x 2.60 x 1.50 in.		
Weight:	370g		

NON-CONTACT AC VOLTAGE DETECTOR (40110N)	
Voltage Detection Rate:	100V AC to 1000V AC
Frequency Range:	50/60Hz
Dimensions:	6.23 x 0.83 x 0.99 in.
Weight:	105g

RECEPTACLE TESTER (40010S)	
Height:	3.43 in.
Width:	1.73 in.
Depth:	0.95 in.



Checks live voltage without contact



**Southwire Company**  
**One Southwire Drive**  
**Carrollton, GA 30119**



**Southwire™**



**Customer Service: 1-855-SWTOOLS (855-798-6657)**

Scan code to see more  
 Southwire Tools

**southwiretools.com**