

4-11/16" Single Gang Device Rings & Covers

Features

- Ideal for exposed work applications, providing an easy method for the installation of electrical devices
- Can be used on any 4-11/16" square box

Applications

- 4-11/16" single gang device rings are used with 4-11/16" square boxes to mount switches, receptacles and devices
- Angled slots on the covers compensate for up to 12° of box misalignment on upright framing members
- 4-11/16" square covers are used to cover 4-11/16" square box wiring and provide a means for access when future conduit runs are required

Standard Material

- Galvanized steel




E195124



Catalog Number	UPC	Description	Depth	Cubic Inches	Ship Case	Weight/Case
DEVICE RINGS						
F1451	014879	Flat	Flat	---	100	18
F1452	014893	Raised 1/4"	1/4"	1.8	100	18
F1453	014619	Raised 1/2"	1/2"	3.8	50	19
F1454	014626	Raised 5/8"	5/8"	4.3	50	20
F1455	014695	Raised 3/4"	3/4"	5.5	50	21
F1456	014749	Raised 1"	1"	7.5	40	21
F1457	014770	Raised 1-1/4"	1-1/4"	9.4	40	21
F1458	014787	Raised 1-1/2"	1-1/2"	11.2	40	23
F1459	014794	Raised 2"	2"	14.4	40	27
COVERS						
C7510	87175	Flat (1) 1/2" KO Hole & (1) Slot	Flat	---	50	31
C7511	86754	Blank flat (2) Hole & (2) Slot	Flat	---	50	31
C7513	86756	Blank flat (1) Hole & (1) Slot	Flat	---	50	31
C7514	86757	1 gang 1/4" raised (2) Hole & (2) Slot	1/4"	---	50	31


4-11/16" Single Gang Device Rings & Covers



F1451




F1455




F1452




F1456




F1453




F1457



F1454



F1458



F1459



C7510



C7511



C7513



C7514
1/4" Raised