

IMAGE COMING SOON

Product Number: 47739

Order Abbreviation: M400/MULTI-KIT

General Description: 120/208/240/277V multi-tap magnetic core and coil ballast for 400W metal halide lamp

*** Full Case Required**

Product Information

Abbrev. With Packaging Info.	M400MULTIKIT 1/CS 1/SKU
ANSI Code	M59
Capacitor Height	3 55/64"
Circuit Type	CWA
Nominal Voltage (V)	120/208/240/277V
Number of Lamps	1
Open Circuit Voltage (V)	300
Power Factor	>0.9
Primary Lamp Type	M400
Sound Rating	N
Starting Method	OCV
Starting Temperature - Fahrenheit	-22°F
Starting Temperature - Celsius	-30°C
Total Harmonic Distortion (THD)	<20%
Wiring Method	LEADS
Total Maximum Wattage	458



Footnotes

- Product is a kit containing the core & coil, capacitor, ignitor (where required), brackets and mounting hardware
- Install in accordance with National Electric Codes
- Ground Ballast Core and Metallic Case of Capacitor and Ignitor
- Minimum starting temperature: -20 F / -29 C
- Product contains installation instructions